

**In the Claims**

Please replace all prior versions, and listings, of claims in the application with the following list of claims:

1. (Currently amended) A variable frequency oscillator comprising:  
a variable frequency oscillator core comprising a plurality of capacitors selectively connectable to a resonant circuit so as to control a frequency of the oscillator;  
an oscillator controller; and  
an output voltage amplitude stabilization device for maintaining an amplitude of an oscillator output within a predetermined range, wherein the variable frequency oscillator core is controllable to operate in one of a plurality of frequency bands and has a frequency control input responsive to the oscillator controller, and where in order to set a new operating frequency the oscillator controller performs a frequency search to set the output frequency of the oscillator by:
  - a) making an adjustment to the frequency of the oscillator by connecting or disconnecting a capacitor from the resonant circuit of the oscillator;
  - b) adjusting an amplitude of oscillation of the oscillator to attain a target value prior to testing the output frequency of the oscillator to compare it to a target frequency;
  - c) comparing the oscillator frequency with a target frequency; and
  - d) on the basis of the comparison repeating steps a) to c) until an appropriate selection of capacitors to be connected to the resonant circuit has been made.~~through the bands to identify an appropriate band and wherein amplitude stabilization is performed during the frequency search through the bands, such that following selection of a frequency band the output voltage stabilization device is operated to control the amplitude of the oscillator to attain a target amplitude prior to testing the operating frequency of the oscillator.~~
2. (Original) A variable frequency oscillator as claimed in claim 1, in which the frequency search is a successive approximation search.
3. (Cancelled)

4. (Original) A variable frequency oscillator as claimed in claim 1, in which the oscillator is in series with a current control device and the magnitude of the current through the current control device can be varied in order to control the amplitude of the output signal of the oscillator, and wherein the current control device is digitally controlled.
5. (Original) A variable frequency oscillator as claimed in claim 4, wherein the current control device comprises a plurality of resistors arranged in parallel, each resistor having an electrically controllable switching device associated with it such that current flow through each resistor can be selectively enabled or inhibited.
6. (Original) A variable frequency oscillator as claimed in claim 4, in which the current control device comprises a plurality of current sources connected in parallel, and the current sources are individually controllable to switch them on or off.
7. (Original) A variable frequency oscillator as claimed in claim 6, in which the current sources are binary weighted.
8. (Original) A variable frequency oscillator as claimed in claim 4, in which the oscillator controller is responsive to a measurement of amplitude of the oscillator, and the oscillator controller adjusts the current in the current control device so as to maintain the amplitude of the oscillator in an acceptable range.
9. (Previously presented) A variable frequency oscillator as claimed in claim 8, in which the oscillator controller selects the current to flow in the oscillator on the basis of a substantially monotonically increasing current until the correct amplitude is reached.
10. (Currently amended) A variable frequency oscillator ~~as claimed in claim 9, in~~  
~~which~~comprising:

a variable frequency oscillator core;  
an oscillator controller; and  
an output voltage amplitude stabilization device for maintaining an amplitude of an oscillator output within a predetermined range,

wherein the variable frequency oscillator core is controllable to operate in one of a plurality of frequency bands and has a frequency control input responsive to the oscillator controller, and where in order to set a new operating frequency the oscillator controller performs a frequency search through the bands to identify an appropriate band and wherein:

a) amplitude stabilization is performed during the frequency search through the bands, such that following selection of a frequency band the output voltage stabilization device is operated to control the amplitude of the oscillator to attain a target amplitude prior to testing the operating frequency of the oscillator;

b) the oscillator is in series with a current control device and the magnitude of the current through the current control device can be varied in order to control the amplitude of the output signal of the oscillator, and wherein the current control device is digitally controlled;

c) the oscillator controller is responsive to a measurement of amplitude of the oscillator, and the oscillator controller adjusts the current in the current control device so as to maintain the amplitude of the oscillator in an acceptable range;

d) the oscillator controller selects the current to flow in the oscillator on the basis of a substantially monotonically increasing current until the correct amplitude is reached; and

e) the oscillator controller performs a coarse search of the current required to reach an acceptable amplitude, and then refines this with a fine search so as to refine the current supplied so as to control the amplitude of the oscillator.

11. (Previously presented) A variable frequency oscillator in which a current in the oscillator controlling the magnitude of oscillation is monotonically increased in steps of a first size until such time as a first target oscillation amplitude is exceeded, in which after the first target oscillation amplitude is exceeded the amplitude is successively increased in steps of a second

step size less than the first step size until such time as the amplitude exceeds a second target amplitude.

12. (Original) A variable frequency oscillator as claimed in claim 11, in which once the first target oscillation amplitude is exceeded the current is decremented.

13. (Original) A variable frequency oscillator as claimed in claim 12, in which the current is decremented by at least the first step size.

14. (Cancelled)

15. (Original) A variable frequency oscillator as claimed in claim 1, in which the oscillator is a voltage controlled oscillator and the oscillator frequency is controlled by a phase locked loop, and wherein a correction factor varying as a function of frequency is applied to the voltage controlled oscillator.

16. (Original) A variable frequency oscillator as claimed in claim 1, in which amplitude stabilization is performed only during tuning of the oscillator via band selection.

17. (Previously presented) A method of setting a frequency of a oscillator having a plurality of capacitors selectively connectable to a resonant circuit of the oscillator to control a frequency of the oscillator and also having an amplitude control, the method comprising performing a frequency search to set the output frequency of the oscillator by repeating the steps of:

- a. making an adjustment to the frequency of the oscillator by connecting or disconnecting a capacitor from the resonant circuit of the oscillator;
- b. adjusting an amplitude of oscillation of the oscillator to attain a target value prior to testing the output frequency of the oscillator to compare it to a target frequency;
- c. comparing the oscillator frequency with a target frequency; and

- d. on the basis of the comparison repeating steps a to c until an appropriate selection of capacitors to be connected to the resonant circuit has been made.
18. (Original) A method as claimed in claim 17, in which the amplitude of oscillation is adjusted using a search procedure in which an adjustment is made to an amplitude control parameter, and the resultant amplitude is measured and a further adjustment of the amplitude control parameter is made if the amplitude has not attained the target amplitude.
19. (Original) A method as claimed in claim 17, in which the amplitude control parameter is increased from a minimum value towards a maximum value until the target amplitude is achieved.
20. (Original) A method as claimed in claim 19, in which a coarse setting procedure is used to find an approximate amplitude by incrementing the amplitude control parameter using a first step size, and once the value has been approximated a fine setting procedure is implemented in which the changes of a second step size, smaller than the first step size, are made to achieve the target amplitude.
21. (Original) A method as claimed in claim 17, in which the oscillator amplitude is controlled by virtue of the current supplied to the oscillator and the current is controlled in a digital manner to control the amplitude of the oscillator.
22. (Original) A method as claimed in claim 21, in which the current is supplied by a plurality of electronically controllable current sources, and the current sources are binary weighted, and selected ones of the current sources are switched on to achieve a desired current.
23. (Previously presented) An amplitude control system for an oscillator, wherein the control system is responsive to measurement of oscillator amplitude and compares this with a target amplitude to derive an amplitude error value, and wherein the amplitude error value is used to

control a digital amplitude controller such that changes in an oscillator amplitude control signal are quantized, wherein the amplitude error value is merely indicative of whether the oscillator amplitude is one of greater than and less than the target amplitude, the control system successively increments the oscillator amplitude from a minimum value to the target value and during a first phase of amplitude control the amplitude control signal is incremented in steps of a first step size until a first acceptable approximation to the target amplitude is achieved, and thereafter a second phase is implemented in which adjustments of a second step size are made to achieve a second acceptable approximation to the target value, the second step size being smaller than the first step size.

24. (Cancelled)

25. (Cancelled)

26. (Cancelled)

27. (Previously presented) An amplitude control system as claimed in claim 23, in which the first acceptable approximation of the target amplitude is smaller than the second acceptable approximation of the target amplitude.

28. (Previously presented) An amplitude control system as claimed in claim 23, in which once the first acceptable approximation is exceeded, the amplitude control signal is decremented by the first step size before proceeding to the second phase.

29. (Original) An amplitude control system as claimed in claim 23, wherein the amplitude control signal is used to drive a digitally controlled current supply device.

30. (Original) An amplitude control system as claimed in claim 29, wherein the digitally controlled current supply device comprises a plurality of current mirrors arranged in parallel, the current mirrors being individually controllable between being on and off.

31. (Original) An amplitude control system as claimed in claim 30, wherein the current mirrors are binary weighted.

32. (Original) An amplitude control system as claimed in claim 29, wherein the digitally controlled current supply device comprises at least one current mirror which is permanently on.

33. (Cancelled)

34. (Cancelled)

35. (Cancelled)

36. (Cancelled)

37. (Cancelled)

38. (Cancelled)

39. (Cancelled)

40. (Cancelled)

41. (Cancelled)

Serial No.: 10/679,997  
Conf. No.: 4552

- 9 -

Art Unit: 2817

42. (Original) A mobile telephone including a voltage controlled oscillator as claimed in claim 1.